


Description

The products are widely used in China and global 4G/5G base station, 5G network coverage, BeiDou navigation antenna, vehicle-mounted high-precision navigation (unmanned) antenna and other applications. The products have miniaturization, low-loss, wide-bandwidth, high power density, high reliability, high cost-effective and other competitive advantages.



Features:

- 1700-2300 MHz
- 4G/5G base station
- High Power
- Very Low Loss
- Tight Amplitude Balance
- High Isolation
- Production Friendly
- Good Repeatability
- CTE compatible with FR4, G-10, RF-35, RO4350B and polyimide
- Immersion gold, prevent surface oxidation & scratch
- RoHS Compliant
- Tape and Reel
- Lead-Free
- Halogen-Free


Electrical Specifications

Frequency	Isolation	Insertion Loss	Return Loss	Amplitude Balance
<i>MHz</i>	<i>dB Min</i>	<i>dB Max</i>	<i>dB</i>	<i>dB Max</i>
1700 -2300	20	0.30	20	± 0.35
1805 -1880	21	0.20	21	± 0.25
1930 -1990	23	0.20	23	± 0.25
Phase Balance	Power	Operating Temp.		
<i>Degrees</i>	<i>Avg. CW Watts at 95 °C</i>	<i>°C</i>		
90 ± 3.0	25	-55 to +140		
90 ± 3.0	25	-55 to +140		
90 ± 3.0	25	-55 to +140		

Notes:


1. All the above data are based on specified demo board.
2. Insertion loss: Thru board loss has been removed.

Mechanical Outline



Hybrid Coupler Pin Configuration

The HC19F03A has an orientation marker to denote Pin1. Once port one has been identified the other ports are known automatically. Please see the chart below for clarification:




Configuration	Pin 1	Pin 2	Pin 3	Pin 4
Splitter	Input	Isolated	-3dB $\angle \theta - 90$	-3dB $\angle \theta$
Splitter	Isolated	Input	-3dB $\angle \theta$	-3dB $\angle \theta - 90$
Splitter	-3dB $\angle \theta - 90$	-3dB $\angle \theta$	Input	Isolated
Splitter	-3dB $\angle \theta$	-3dB $\angle \theta - 90$	Isolated	Input
*Combiner	A $\angle \theta - 90$	A $\angle \theta$	Isolated	Output
*Combiner	A $\angle \theta$	A $\angle \theta - 90$	Output	Isolated
*Combiner	Isolated	Output	A $\angle \theta - 90$	A $\angle \theta$
*Combiner	Output	Isolated	A $\angle \theta$	A $\angle \theta - 90$

*Note: "A" is the amplitude of the applied signals. When two quadrature signals with equal amplitudes are applied to the coupler as described in the table, they will combine at the output port. If the amplitudes are not equal, some of the applied energy will be directed to the isolated port.


Typical Performance Data (@25°C)

Frequency (MHz)	Coupling (dB)	Transmission (dB)	Insertion Loss (dB)	Isolation (dB)	Amplitude Balance (dB)	Phase (degree)	Return Loss(dB)			
							S11	S22	S33	S44
1700	-3.25	-3.00	-0.11	-21.16	-0.12	-90.04	-22.10	-22.10	-22.34	-22.12
1730	-3.30	-3.10	-0.19	-21.44	-0.10	-90.05	-22.11	-22.17	-22.38	-22.30
1760	-3.14	-3.00	-0.06	-21.52	-0.07	-90.29	-22.11	-22.20	-22.45	-22.31
1790	-3.18	-3.12	-0.14	-21.76	-0.03	-90.24	-22.06	-22.16	-22.40	-22.42
1820	-3.16	-3.13	-0.13	-21.89	-0.02	-90.33	-22.05	-22.17	-22.36	-22.51
1850	-3.06	-3.10	-0.07	-22.02	0.02	-90.48	-21.97	-22.14	-22.28	-22.52
1880	-3.14	-3.21	-0.16	-22.24	0.04	-90.46	-21.75	-22.08	-22.18	-22.53
1910	-3.07	-3.18	-0.12	-22.30	0.05	-90.58	-21.72	-22.08	-22.13	-22.55
1940	-3.13	-3.27	-0.19	-22.43	0.07	-90.61	-21.52	-22.08	-22.02	-22.60
1970	-3.05	-3.20	-0.11	-22.41	0.08	-90.78	-21.27	-21.89	-21.90	-22.45
2000	-2.98	-3.18	-0.07	-22.36	0.10	-91.01	-21.16	-21.74	-21.68	-22.42
2030	-3.10	-3.32	-0.20	-22.46	0.11	-91.00	-20.88	-21.63	-21.57	-22.38
2060	-2.98	-3.21	-0.08	-22.24	0.11	-91.30	-20.68	-21.38	-21.42	-22.16
2090	-2.99	-3.26	-0.11	-22.19	0.13	-91.33	-20.47	-21.13	-21.15	-22.01
2120	-3.04	-3.30	-0.16	-22.11	0.13	-91.36	-20.21	-21.02	-20.98	-21.85
2150	-3.04	-3.30	-0.16	-21.90	0.13	-91.56	-20.03	-20.81	-20.71	-21.64
2180	-3.01	-3.27	-0.13	-21.67	0.13	-91.68	-19.74	-20.50	-20.44	-21.34
2210	-2.98	-3.24	-0.10	-21.37	0.12	-91.90	-19.57	-20.21	-20.19	-21.08
2240	-3.16	-3.42	-0.28	-21.22	0.13	-91.98	-19.33	-19.98	-19.89	-20.92
2270	-3.03	-3.26	-0.13	-20.78	0.11	-92.13	-19.09	-19.68	-19.62	-20.60
2300	-3.08	-3.30	-0.18	-20.44	0.11	-92.36	-18.94	-19.41	-19.28	-20.39

Typical Performance (-55°C, 25°C, 95°C, 125°C: 1700-2300 MHz)



Typical Performance (-55°C, 25°C, 95°C, 125°C: 1700-2300 MHz)



Definition of Measured Specifications

Parameter	Definition	Mathematical Representation
VSWR (Voltage Standing Wave Ratio)	The impedance match of the coupler to a 50Ω system. A VSWR of 1:1 is optimal.	$VSWR = \frac{V_{max}}{V_{min}}$ Vmax = voltage maxima of a standing wave Vmin = voltage minima of a standing wave
Return Loss	The impedance match of the coupler to a 50Ω system. Return Loss is an alternate means to express VSWR.	$\text{Return Loss (dB)} = 20 \log \frac{VSWR + 1}{VSWR - 1}$
Insertion Loss	The input power divided by the sum of the power at the two output ports.	$\text{Insertion Loss(dB)} = 10 \log \frac{P_{in}}{P_{cpl} + P_{transmission}}$
Isolation	The input power divided by the power at the isolated port.	$\text{Isolation(dB)} = 10 \log \frac{P_{in}}{P_{iso}}$
Phase Balance	The difference in phase angle between the two output ports.	Phase at coupled port – Phase at transmission port
Amplitude Balance	The power at each output divided by the average power of the two outputs.	$10 \log \frac{P_{cpl}}{\left(\frac{P_{cpl} + P_{transmission}}{2}\right)} \quad \text{or} \quad 10 \log \frac{P_{transmission}}{\left(\frac{P_{cpl} + P_{transmission}}{2}\right)}$


Test Method

1. Calibrating your vector network analyzer.
2. Connect the VNA 4 Port to DUT respectively.
3. Measure the data of coupling through port 1 to port 4(S41).
4. Measure the data of transmission through port 1 to port 3(S31).
5. Measure the data of isolation through port 1 to port 2(S21).
6. Measure the data of phase port 4 & port 3(port 1 feeding).
7. Measure the data of return loss port 1, port 2, port 3 & port 4.
8. According to the above data to calculate insertion loss, amplitude balance & phase.


Note:

1. When calculating insertion loss at room temperature, demo board loss should be removed from both coupling & transmission data. Please refer to the below table for demo board loss :

Frequency Range(MHz)	Demo Board Loss (dB) @25°C
470-860	0.07
800-1000	0.10
1200-1700	0.15
1700-2000	0.15
2000-2300	0.20
2300-2700	0.25




Recommended PCB Layout




NOTE:

1. 50Ω line width is shown above designing from $\epsilon_r=3.66$ THK=0.762mm copper 1 OZ
2. Bottom side of the PCB is continuous ground plane.
3. All dimensions shown in mm [inch].


Reflow Profile



Reliability Test Flow




Reliability Test Flow



Tape and Reel Drawing


Feeding Direction



ITEM	W	A0	B0	K0	K1	P	F	E	D	P0	P2	t	7"
DIM(mm)	12.0	3.45	5.35	1.5		8	5.5	1.75	1.50	4.00	2.00	0.30	P/R
TOLE	+0.30 -0.30	+0.10 -0.10	+0.10 -0.00	+0.10 -0.10	+0.10 -0.10	+0.05 -0.05	1000pcs						

Notice:

- A.10 Sprocket hole pitch cumulative tolerance is 0.2mm.
- B. Carrier camber shall be not more than 1mm per 100mm through a length of 250mm.
- C. All dimensions meet EIA-418-B requirements.
- D. A0 & B0 measured as indicated.
- E. K0 measured from a place on the inside bottom of the pocket to top surface of carrier.
- F. Material: PE 100
- G. Thickness: 0.30±0.05mm
- H. 1000 units (maximum) / T&R



Symbol	Dimensions(mm)
W	12.5±0.4
A	177±0.5
N	63±0.3
T	1.8±0.2
E	2.1±0.3
F	10.75±0.3
D	13.5+0.5/-0.2

